

1 Description

The iW600 is a secondary-side voltage position controller to detect the voltage undershoot. It can be used in Dialog's primary-side control systems to achieve ultra-low no-load power consumption and fast dynamic load response. The iW600 operates in "Normally-OFF" mode with negligible power consumption during power supply normal steady state operation, while monitoring dynamic load change through the voltage on the secondary rectifier. A wake-up signal is transferred through the flyback power transformer to the primary side when a dynamic load change is detected. The iW600 eliminates loop compensation components and the optocoupler on the secondary side to minimize the bill of material cost.

2 Features

- Fast system output voltage detection
- Transmits detection signal to the primary side through flyback transformer
- Two-electrical-terminal connection simplifies system PCB layout
- No external components
- Enables <10mW no-load power consumption in typical 5V-output systems
- Available in 3-lead SOT-23 and 2-lead DFN packages

3 Applications

AC/DC adapters/chargers





Figure 3.1: iW600 Typical Application Circuit (Using iW1600 as Primary-Side Controller) (Achieving < 10mW No-load Power Consumption in 5V/2A 10W Adapter with Fast Dynamic Load Response)



4 Pinout Description






Figure 4.1: 3-Lead SOT-23 Package

Figure 4.2: 2-Lead DFN Package

Pin No.	Name	Туре	Pin Description
1	STR	Power Input/ Analog Input/ Power Output	Stroke pin. Controller Power input and voltage monitoring input. It also builds in a open-drain circuit to drive the flyback power transformer when dynamic load is detected.
2	GND	Ground	Ground.
3	N/C	N/C	Not connected. Recommend design a solder pad and solder this pin on the printed circuit board for mechanical stability.

Note 1: The N/C pin is only available in the 3-lead SOT-23 package.



5 Absolute Maximum Ratings


Absolute maximum ratings are the parameter values or ranges which can cause permanent damage if exceeded. For maximum safe operating conditions, refer to Electrical Characteristics (Section 6).

Parameter	Symbol	Value	Units
Input voltage range	V_{STR}	-1 to 60	V
Continuous DC supply current at V_{STR} pin (V_{STR} = 60V)	I _{CC_OP}	1	mA
Open-draining pull-down pulse current (V _{STR} = 40V)		400	mA
Maximum junction temperature	T _{JMAX}	150	°C
Operating junction temperature	T _{JOPT}	-40 to 150	°C
Storage temperature	T _{STG}	-65 to 150	°C
Thermal resistance junction-to-ambient (SOT-23)	θ_{JA}	260	°C/W
Thermal resistance junction-to-ambient (DFN)	θ_{JA}	680	°C/W
ESD rating per JEDEC JS-001-2017		±2,000	V



6 Physical Dimensions

3-Lead SOT-23 Package



Symbol	Incl	hes	Millimeters		
Syr	MIN	MAX	MIN	MAX	
Α	0.035	0.044	0.89	1.11	
A1	0.001	0.004	0.01	0.10	
В	0.015	0.020	0.37	0.50	
С	0.003	0.007	0.09	0.18	
D	0.110	0.120	2.80	3.04	
Е	0.083	0.104	2.10	2.64	
E1	0.047	0.081	1.20	1.40	
e1	0.070	0.020	1.78	2.04	

Compliant to JEDEC Standard TO236

Controlling dimensions are in millimeters

This package is RoHS compliant, and conform to Halide free limits.


Soldering Temperature Resistance:

- [a] Package is IPC/JEDEC Std 020D Moisture Sensitivity Level 1
- [b] Package exceeds JEDEC Std No. 22-A111 for Solder Immersion resistance; packages can withstand 10 s immersion @ < 260 °C</p>

Dimension D does not include mold flash, protrusions or gate burrs. Mold flash, protrusions or gate burrs shall not exceed 0.25 mm per end. Dimension E1 does not include interlead flash or protrusion. Interlead flash or protrusion shall not exceed 0.25 mm per side.



2-Lead DFN Package



	MILLIMETERS				
	MIN	NOM	MAX		
Α	0.70	0.75	0.80		
A1	0.00	-	0.05		
A2	0.203 REF				
b	0.85	0.90	0.95		
D	1.25	1.30	1.35		
е	1.00 BSC				
Е	1.65	1.70	1.75		
L1	0.30	0.40	2.50		
L2	0.90	1.00	1.10		

All dimensions are in millimeters.

Coplanarity applies to the exposed pad as well as the terminals.

Coplanarity shall not exceed 0.05 millimeters.

Warpage shall not exceed 0.05 millimeters.

Soldering Temperature Resistance:

- [a] Package is IPC/JEDEC Std 020D Moisture Sensitivity Level 1.
 [b] Package exceeds JEDEC Std No. 22-A111 for Solder Immersion Resistance; package can withstand 10 seconds immersion < 260°C.

7 Ordering Information

Part Number	Options	Package	Description
iW600-00-ST3	N/A	SOT-23L-3L	Tape & Reel ¹
iW600-00-DFN2	N/A	DFN-1.3m-2L	Tape & Reel¹

Note 1: Tape & Reel packing quantity is 3,000/reel. Minimum packing quantity is 3,000.



Disclaimer

Unless otherwise agreed in writing, the Dialog Semiconductor products (and any associated software) referred to in this document are not designed, authorized or warranted to be suitable for use in life support, life-critical or safety-critical systems or equipment, nor in applications where failure or malfunction of a Dialog Semiconductor product (or associated software) can reasonably be expected to result in personal injury, death or severe property or environmental damage. Dialog Semiconductor and its suppliers accept no liability for inclusion and/or use of Dialog Semiconductor products (and any associated software) in such equipment or applications and therefore such inclusion and/or use is at the customer's own risk.

Information in this document is believed to be accurate and reliable. However, Dialog Semiconductor does not give any representations or warranties, express or implied, as to the accuracy or completeness of such information. Dialog Semiconductor furthermore takes no responsibility whatsoever for the content in this document if provided by any information source outside of Dialog Semiconductor.

Dialog Semiconductor reserves the right to change without notice the information published in this document, including, without limitation, the specification and the design of the related semiconductor products, software and applications. Notwithstanding the foregoing, for any automotive grade version of the device, Dialog Semiconductor reserves the right to change the information published in this document, including, without limitation, the specification and the design of the related semiconductor products, software and applications, in accordance with its standard automotive change notification process.

Applications, software, and semiconductor products described in this document are for illustrative purposes only. Dialog Semiconductor makes no representation or warranty that such applications, software and semiconductor products will be suitable for the specified use without further testing or modification. Unless otherwise agreed in writing, such testing or modification is the sole responsibility of the customer and Dialog Semiconductor excludes all liability in this respect.

Nothing in this document may be construed as a license for customer to use the Dialog Semiconductor products, software and applications referred to in this document. Such license must be separately sought by customer with Dialog Semiconductor.

All use of Dialog Semiconductor products, software and applications referred to in this document is subject to Dialog Semiconductor's Standard Terms and Conditions of Sale, available on the company website (www.dialog-semiconductor.com) unless otherwise stated.

Dialog, Dialog Semiconductor and the Dialog logo are trademarks of Dialog Semiconductor Plc or its subsidiaries. All other product or service names and marks are the property of their respective owners.

© 2021 Dialog Semiconductor. All rights reserved.

RoHS Compliance

Dialog Semiconductor's suppliers certify that its products are in compliance with the requirements of Directive 2011/65/EU of the European Parliament on the restriction of the use of certain hazardous substances in electrical and electronic equipment. RoHS certificates from our suppliers are available on request.

Contacting Dialog Semiconductor

United Kingdom (Headquarters)
Dialog Semiconductor (UK) LTD

Phone: +44 1793 757700

Germany

Dialog Semiconductor GmbH Phone: +49 7021 805-0

The Netherlands

Dialog Semiconductor B.V. Phone: +31 73 640 8822

Email

info_pcbg@diasemi.com

North America

Dialog Semiconductor Inc. Phone: +1 408 845 8500

Japan

Dialog Semiconductor K. K. Phone: +81 3 5769 5100

Taiwan

Dialog Semiconductor Taiwan Phone: +886 281 786 222

Web site:

www.dialog-semiconductor.com

Hong Kong

Dialog Semiconductor Hong Kong Phone: +852 2607 4271

Korea

Dialog Semiconductor Korea Phone: +82 2 3469 8200 China (Shenzhen)

Dialog Semiconductor China Phone: +86 755 2981 3669

China (Shanghai)

Dialog Semiconductor China Phone: +86 21 5424 9058

Product Summary Rev. 1.2 14-Mar-2021